

## Automatic Wire Feeder

### RSE-WF-1235



### Feature

- ▶ Suitable for all automatic wire processing center and wire cutting&stripping machine.
- ▶ Forward and reverse wire feeding direction, switchable as needed.
- ▶ No wire tangling and snarling guaranteed by built-in microcontroller.
- ▶ Automatically detects and feeds the required wire length.

### Specification

Model	RSE-WF-1235
Feeding Direction	Forward/Reverse
Application	Feed wire for automatic wire processing center and wire cutting&stripping machine.
Applicable Cable	All electronic wires, excluding flat ribbon cables.
Recipe	10 groups
Cable O.D.	12-32mm
Load Capacity	15kg
Voltage	AC220V
Weight	8.8KG
Spool I.D.	350mm
Spool O.D.	380mm
Spindle O.D.	120mm
Overall Dimension	L390mm×W390mm×H500mm